Lenovo Chromebook Duet (11", 9) Lenovo Chromebook Duet EDU G2 Hardware Maintenance Manual



First Edition (August 2024)

© Copyright Lenovo 2024.

# **Contents**

| About this manual iii                                | Remove the kickstand (for LNV Chrome Duet EDU G2)  | 30   |
|--|--|------|
| Chapter 1. Safety information 1                      | Remove the LCD module  |      |
| General safety                                       | Remove the EDP cable   | 32   |
| Electrical safety                                    | Remove the battery pack  | 33   |
| Safety inspection guide                              | Remove the pogo pin bracket  |      |
| Handling devices that are sensitive to electrostatic | Remove the pogo pin cable  | 36   |
| discharge  | Remove the system board USB Type-C mylar   | 37   |
| Grounding requirements 4                             | Remove the system board USB Type-C bracket   | 38   |
| Safety notices (multilingual translations) 4         | Remove the speakers  | 38   |
| Chantar 9 Canaral abackaut 91                        | Remove the antenna module  | 40   |
| Chapter 2. General checkout 21                       | Remove the I/O board bracket   | 41   |
| What to do first                                     | Remove the I/O board   | 41   |
| CRU list   | Remove the USB Type-C cable and audio cable  | 43   |
| Chapter 3. Create and use a USB                      | Remove the power and volume board and cable  | 44   |
| repair shim 23                                       | Remove the camera cover, camera cover bracket, camera LED cable, and front-facing camera | 45   |
| What is a USB repair shim?                           | Remove the microphone cables   | 47   |
| Chapter 4. Identifying FRUs                          | Remove the rear-facing camera bracket  | 48   |
| (CRUs)   | Remove the rear-facing camera  | 49   |
| Locate FRUs and CRUs                                 | Remove the system board  | 50   |
|  | Remove the LCD cover   | 51   |
| Chapter 5. Removing a FRU or                         |  |      |
| CRU 29   | Chapter 6. Label locations   |      |
| Service tools  | Trademarks   | . Iv |
| General guidelines                                   |  |      |

# **About this manual**

This manual contains service and reference information for the following Lenovo products.

| Machine                  | Machine type (MT) |
|--------------------------|-------------------|
| LNV CB Duet 11M889       |                   |
| LNV CB Duet 11M889 1     | 83HH              |
| LNV CB Duet 11M889 2     |                   |
| LNV Chrome Duet EDU G2   |                   |
| LNV Chrome Duet EDU G2 1 | 83HJ, 83HK        |
| LNV Chrome Duet EDU G2 2 |                   |

### Important:

- This manual is intended only for trained service technicians who are familiar with Lenovo products.
- Before servicing a Lenovo product, be sure to read all the information under Chapter 1 "Safety information" on page 1.

# **Chapter 1. Safety information**

This chapter presents the following safety information that you need to be familiar with before you service a Lenovo Chromebook.

### **General safety**

Follow these rules to ensure general safety:

- Observe good housekeeping in the area of the machines during and after maintenance.
- When lifting any heavy object:
  - 1. Make sure that you can stand safely without slipping.
  - 2. Distribute the weight of the object equally between your feet.
  - 3. Use a slow lifting force. Never move suddenly or twist when you attempt to lift.
  - 4. Lift by standing or by pushing up with your leg muscles; this action removes the strain from the muscles in your back. Do not attempt to lift any object that weighs more than 16 kg (35 lb) or that you think is too heavy for you.
- Do not perform any action that causes hazards to the customer, or that makes the equipment unsafe.
- Before you start the machine, make sure that other service technicians and the customer's personnel are not in a hazardous position.
- Place removed covers and other parts in a safe place, away from all personnel, while you are servicing the
  machine.
- Keep your tool case away from walk areas so that other people will not trip over it.
- Do not wear loose clothing that can be trapped in the moving parts of a machine. Make sure that your sleeves are fastened or rolled up above your elbows. If your hair is long, fasten it.
- Insert the ends of your necktie or scarf inside clothing or fasten it with a non-conductive clip, about 8 centimeters (3 inches) from the end.
- Do not wear jewelry, chains, metal-frame eyeglasses, or metal fasteners for your clothing.

**Attention:** Metal objects are good electrical conductors.

- Wear safety glasses when you are hammering, drilling, soldering, cutting wire, attaching springs, using solvents, or working in any other conditions that might be hazardous to your eyes.
- After service, reinstall all safety shields, guards, labels, and ground wires. Replace any safety device that is worn or defective.
- Reinstall all covers correctly before returning the machine to the customer.
- Fan louvers on the machine help to prevent overheating of internal components. Do not obstruct fan louvers or cover them with labels or stickers.

# **Electrical safety**

Observe the following rules when working on electrical equipment.

**Important:** Use only approved tools and test equipment. Some hand tools have handles covered with a soft material that does not insulate you when working with live electrical currents. Many customers have, near their equipment, rubber floor mats that contain small conductive fibers to decrease electrostatic discharges. Do not use this type of mat to protect yourself from electrical shock.

- Find the room emergency power-off (EPO) switch, disconnecting switch, or electrical outlet. If an electrical accident occurs, you can then operate the switch or unplug the power cord quickly.
- Do not work alone under hazardous conditions or near equipment that has hazardous voltages.
- Disconnect all power before:
  - Performing a mechanical inspection
  - Working near power supplies

- Removing or installing main units
- Before you start to work on the machine, unplug the power cord. If you cannot unplug it, ask the customer to power-off the wall box that supplies power to the machine, and to lock the wall box in the off position.
- If you need to work on a machine that has exposed electrical circuits, observe the following precautions:
  - Ensure that another person, familiar with the power-off controls, is near you.

**Attention:** Another person must be there to switch off the power, if necessary.

- Use only one hand when working with powered-on electrical equipment; keep the other hand in your pocket or behind your back.

Attention: An electrical shock can occur only when there is a complete circuit. By observing the above rule, you may prevent a current from passing through your body.

- When using testers, set the controls correctly and use the approved probe leads and accessories for that tester.
- Stand on suitable rubber mats (obtained locally, if necessary) to insulate you from grounds such as metal floor strips and machine frames.

Observe the special safety precautions when you work with very high voltages; Instructions for these precautions are in the safety sections of maintenance information. Use extreme care when measuring high voltages.

- Regularly inspect and maintain your electrical hand tools for safe operational condition.
- Do not use worn or broken tools and testers.
- Never assume that power has been disconnected from a circuit. First, check that it has been powered off.
- Always look carefully for possible hazards in your work area. Examples of these hazards are moist floors, non-grounded power extension cables, power surges, and missing safety grounds.
- Do not touch live electrical circuits with the reflective surface of a plastic dental mirror. The surface is conductive; such touching can cause personal injury and machine damage.
- Do not service the following parts with the power on when they are removed from their normal operating places in a machine:
  - Power supply units
  - Pumps
  - Blowers and fans
  - Motor generators
  - Similar units as listed above

This practice ensures correct grounding of the units.

- If an electrical accident occurs:
  - Use caution; do not become a victim yourself.
  - Switch off power.
  - Send another person to get medical aid.

# Safety inspection guide

The purpose of this inspection guide is to assist you in identifying potentially unsafe conditions. As each machine was designed and built, required safety items were installed to protect users and service technicians from injury. This guide addresses only those items. You should use good judgment to identify potential safety hazards due to attachment of non-Lenovo features or options not covered by this inspection guide.

If any unsafe conditions are present, you must determine how serious the apparent hazard could be and whether you can continue without first correcting the problem.

Consider these conditions and the safety hazards they present:

- Electrical hazards, especially primary power (primary voltage on the frame can cause serious or fatal electrical shock)
- Explosive hazards, such as a damaged cathode ray tube (CRT) face or a bulging capacitor
- Mechanical hazards, such as loose or missing hardware

To determine whether there are any potentially unsafe conditions, use the following checklist at the beginning of every service task. Begin the checks with the power off, and the power cord disconnected.

#### Checklist:

- 1. Check exterior covers for damage (loose, broken, or sharp edges).
- 2. Power off the Chromebook. Disconnect the power cord.
- 3. Check the power cord for:
  - a. A third-wire ground connector is in good condition. Use a meter to measure third-wire ground continuity for 0.1 ohm or less between the external ground pin and the frame ground.
  - b. The power cord should be the authorized type specified for your Chromebook. Go to: http:// www.lenovo.com/serviceparts-lookup
  - c. Insulation must not be frayed or worn.
- 4. Check for cracked or bulging batteries.
- Remove the cover.
- 6. Check for any obvious non-Lenovo alterations. Use good judgment as to the safety of any non-Lenovo alterations.
- 7. Check inside the unit for any obvious unsafe conditions, such as metal filings, contamination, water or other liquids, or signs of fire or smoke damage.
- 8. Check for worn, frayed, or pinched cables.
- 9. Check that the power-supply cover fasteners (screws or rivets) have not been removed or tampered with.

### Handling devices that are sensitive to electrostatic discharge

Any Chromebook part containing transistors or integrated circuits (ICs) should be considered sensitive to electrostatic discharge (ESD). ESD damage can occur when there is a difference in charge between objects. Protect against ESD damage by equalizing the charge so that the machine, the part, the work mat, and the person handling the part are all at the same charge.

#### Notes:

- 1. Use product-specific ESD procedures when they exceed the requirements noted here.
- 2. Make sure that the ESD protective devices you use have been certified (ISO 9000) as fully effective.

#### When handling ESD-sensitive parts:

- Keep the parts in protective packages until they are inserted into the product.
- Avoid contact with other people.
- Wear a grounded wrist strap against your skin to eliminate static on your body.
- Prevent the part from touching your clothing. Most clothing is insulative and retains a charge even when you are wearing a wrist strap.
- Use a grounded work mat to provide a static-free work surface. The mat is especially useful when handling ESD-sensitive devices.
- Select a grounding system, such as those listed below, to provide protection that meets the specific service requirement.

**Note:** The use of a grounding system to guard against ESD damage is desirable but not necessary.

- Attach the ESD ground clip to any frame ground, ground braid, or green-wire ground.
- When working on a double-insulated or battery-operated system, use an ESD common ground or reference point. You can use coax or connector-outside shells on these systems.
- Use the round ground prong of the ac plug on ac-operated Chromebooks.

## **Grounding requirements**

Electrical grounding of the Chromebook is required for operator safety and correct system function. Proper grounding of the electrical outlet can be verified by a certified electrician.

# Safety notices (multilingual translations)

The safety notices in this section are provided in the following languages:

- English
- Arabic
- Brazilian Portuguese
- French
- German
- Hebrew
- Japanese
- Korean
- Spanish
- Traditional Chinese



#### **DANGER**

Before the computer is powered on after FRU replacement, make sure that all screws, springs, and other small parts are in place and are not left loose inside the computer. Verify this by shaking the computer and listening for rattling sounds. Metallic parts or metal flakes can cause electrical short circuits.



#### **DANGER**

Some standby batteries contain a small amount of nickel and cadmium. Do not disassemble a standby battery, recharge it, throw it into fire or water, or short-circuit it. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.



#### **DANGER**

The battery pack contains small amounts of nickel. Do not disassemble it, throw it into fire or water, or short-circuit it. Dispose of the battery pack as required by local ordinances or regulations. Use only the battery in the appropriate parts listing when replacing the battery pack. Use of an incorrect battery can result in ignition or explosion of the battery.



#### **DANGER**

The lithium battery can cause a fire, an explosion, or a severe burn. Do not recharge it, remove its polarized connector, disassemble it, heat it above 100°C (212°F), incinerate it, or expose its cell contents to water. Dispose of the battery as required by local ordinances or regulations. Use only the battery in the appropriate parts listing. Use of an incorrect battery can result in ignition or explosion of the battery.



#### **DANGER**

If the LCD breaks and the fluid from inside the LCD gets into your eyes or on your hands, immediately wash the affected areas with water for at least 15 minutes. Seek medical care if any symptoms from the fluid are present after washing.



#### **DANGER**

To avoid shock, do not remove the plastic cover that protects the lower part of the inverter card.



#### **DANGER**

Though the main batteries have low voltage, a short-circuited or grounded battery can produce enough current to burn personnel or combustible materials.



#### **DANGER**

Unless hot swap is allowed for the FRU being replaced, do as follows before removing it: power off the computer, unplug all power cords from electrical outlets, remove the battery pack, and disconnect any interconnecting cables.



قبل اعادة تشغيل الحاسب بعد الانتهاء من استبدال FRU، تأكد من أنه قد تم اعادة كل من المسامير و السوست وكل الأجزاء الصغيرة الأخرى في أماكنهم ولم يتم فقدهم داخل الحاسب. ويمكن التحقق من ذلك عن طريق هز الحاسب والاستماع لأي صوت صاخب يصدر منه. قد تؤدي الأجزاء أو الرقائق المعدنية الى حدوث دائرة قصر.



تحتوي بعض البطاريات الاحتباطية على كمية صغيرة من مادتي النيكل والكادميوم. لا تقم بقك أو اعادة شحن البطارية الاحتباطية ولا تقم أيضا بالقاءها في النار أو الماء ولا تتسبب في احداث دائرة قصر بها. قم بالتخلص من البطارية كما هو موضح في القوانين المحلية. استخدم نوع البطارية المحدد والذي يوصى باستخدامه. حيث أنه قد يؤدي استخدام نوع بطارية غير صحيح الى اشتعالها أو انفجارها.



تحتوي حزمة البطارية على كمية صغيرة من مادة النيكل. لا تقم بقكها أو القاءها في النار أو الماء ولا تتسبب في احداث دائرة قصر بها. تخلص من حزمة البطارية وفقا لما هو موضح في القوانين المحلية. قم، عند استبدال حزمة البطارية، باستخدام الأنواع المحددة فقط والتي يوصى باستخدامها. حيث أنه قد يودي استخدام نوع بطارية غير صحيح الى اشتعالها أو انفجارها.



قد تتسبب بطارية الليثيوم في حدوث حريق أو انفجار أو حدوث حروق شديدة. لا تقم باعادة شحن البطارية أو ازالة موصل الاستقطاب الخاص بها ولا تحاول أيضا فكها أو تسخينها لأكثر من ١٠٠ درجة منوية (٢١٧ فهرنهايت) أو حرقها أو تعريض محتويات الخانة الخاصة بها للماء. قم بالتخلص من البطارية وفقا لما هو موضح في القوانين المحلية. استخدم نوع البطارية المحدد والذي يوصى باستخدامه. حيث أنه قد يؤدي استخدام نوع بطارية غير صحيح الى اشتعالها أو انفجارها.



اذا ما انكسرت شاشة LCD ولامس السائل الداخلي عينيك أو يديك، قم في الحال بغسلهما بالماء لمدة لا تقل عن ١٥ دقيقة. اذا ما وجدت أي أعراض بعد الغسل اطلب عندئذ المساعدة الطبية.



لتجنب التعرض لأي صدمات، لا تقم بازالة الغطاء البلاستيكي الذي يحمي الجزء الأسفل من بطاقة العاكس.



على الرغم من أن البطاريات الرئيسية يكون لها جهد منخفض، الا أنه قد تقوم البطاريات التي حدث قصور بها أو التي توصيلها أرضيا باصدار تيار يكفي لحدوث حروق للأفراد أو تعرض المواد القابلة للاشتعال للحريق.



ما لم يتم السماح بالتبديل الفوري لأي FRU الجاري استبداله بدون ضرورة اغلاق النظام، قم بتنفيذ ما يلي قبل ازالته، قم بايقاف تشغيل الحاسب ونزع كل أسلاك الطاقة من المخارج الكهربائية وقم أيضا بازالة حزمة البطارية ثم قم بفصل أي كابلات متصلة.



#### **PERIGO**

Antes de ligar o computador após a substituição da FRU, certifique-se de que todos os parafusos, molas e outras peças pequenas estejam no lugar e não estejam soltos dentro do computador. Verifique isso sacudindo o computador e procurando ouvir sons de peças soltas. Peças metálicas ou lascas de metal podem causar curto-circuito.



#### **PERIGO**

Algumas baterias reserva contêm uma pequena quantidade de níquel e cádmio. Não desmonte uma bateria reserva, recarregue-a, jogue-a no fogo ou na água, ou deixe-a entrar em curto-circuito. Descarte a bateria conforme requerido pelas leis ou regulamentos locais. Use somente a bateria nas partes listadas apropriadas. O uso de uma bateria incorreta pode resultar em combustão ou explosão da bateria.



#### **PERIGO**

O pacote da bateria contém uma pequena quantidade de níquel. Não o desmonte, jogue-o no fogo ou na água, ou deixe-o entrar em curto-circuito. Descarte o pacote da bateria conforme requerido pelas leis ou regulamentos locais. Use somente a bateria nas partes listadas apropriadas ao substituir o pacote da bateria. O uso de uma bateria incorreta pode resultar em combustão ou explosão da bateria.



#### **PERIGO**

A bateria de lítio pode causar incêndio, explosão ou graves queimaduras. Não a recarregue, remova seu conector polarizado, desmonte-a, aqueça-a acima de 100°C (212°F), incinere-a, ou exponha o conteúdo de sua célula à água. Descarte a bateria conforme requerido pelas leis ou regulamentos locais. Use somente a bateria nas partes listadas apropriadas. O uso de uma bateria incorreta pode resultar em combustão ou explosão da bateria.



#### **PERIGO**

Se o LCD quebrar e o fluido de dentro dele entrar em contato com seus olhos ou com suas mãos, lave as áreas afetadas imediatamente com água durante pelo menos 15 minutos. Procure cuidados médicos se algum sintoma causado pelo fluido surgir após a lavagem.



### PERIGO

Para evitar choque elétrico, não remova a capa plástica que protege a parte inferior da placa inversora.



#### **PERIGO**

Embora as principais baterias possuam baixa voltagem, uma bateria em curto-circuito ou aterrada pode produzir corrente o bastante para queimar materiais de pessoal ou inflamáveis.



#### **PERIGO**

A menos que uma hot swap seja permitida para a FRU que está sendo substituída, faça o seguinte antes de removê-la: desligue o computador, desconecte todos os cabos de energia das tomadas, remova o pacote de baterias e desconecte quaisquer cabos de interconexão.



#### **DANGER**

Avant de remettre l'ordinateur sous tension après remplacement d'une unité en clientèle, vérifiez que tous les ressorts, vis et autres pièces sont bien en place et bien fixées. Pour ce faire, secouez l'unité et assurez-vous qu'aucun bruit suspect ne se produit. Des pièces métalliques ou des copeaux de métal pourraient causer un court-circuit.



#### **DANGER**

Certaines batteries de secours contiennent du nickel et du cadmium. Ne les démontez pas, ne les rechargez pas, ne les exposez ni au feu ni à l'eau. Ne les mettez pas en court-circuit. Pour les mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la pile de sauvegarde ou celle de l'horloge temps réel, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. Une batterie ou une pile inappropriée risque de prendre feu ou d'exploser.



#### **DANGER**

La batterie contient du nickel. Ne la démontez pas, ne l'exposez ni au feu ni à l'eau. Ne la mettez pas en court-circuit. Pour la mettre au rebut, conformez-vous à la réglementation en vigueur. Lorsque vous remplacez la batterie, veillez à n'utiliser que les modèles cités dans la liste de pièces détachées adéquate. En effet, une batterie inappropriée risque de prendre feu ou d'exploser.



### **DANGER**

La pile de sauvegarde contient du lithium. Elle présente des risques d'incendie, d'explosion ou de brûlures graves. Ne la rechargez pas, ne retirez pas son connecteur polarisé et ne la démontez pas. Ne l'exposez pas à une temperature supérieure à 100°C, ne la faites pas brûler et n'en exposez pas le contenu à l'eau. Mettez la pile au rebut conformément à la réglementation en vigueur. Une pile inappropriée risque de prendre feu ou d'exploser.



#### **DANGER**

Si le panneau d'affichage à cristaux liquides se brise et que vous recevez dans les yeux ou sur les mains une partie du fluide, rincez-les abondamment pendant au moins quinze minutes. Consultez un médecin si des symptômes persistent après le lavage.



#### DANGER

Afin d'éviter tout risque de choc électrique, ne retirez pas le cache en plastique protégeant la partie inférieure de la carte d'alimentation.



#### **DANGER**

Bien que le voltage des batteries principales soit peu élevé, le court-circuit ou la mise à la masse d'une batterie peut produire suffisamment de courant pour brûler des matériaux combustibles ou causer des brûlures corporelles graves.



#### **DANGER**

Si le remplacement à chaud n'est pas autorisé pour l'unité remplaçable sur site que vous remplacez, procédez comme suit avant de retirer l'unité : mettez l'ordinateur hors tension, débranchez tous les cordons d'alimentation des prises de courant, retirez le bloc de batterie et déconnectez tous les câbles d'interconnexion.



#### VORSICHT

Bevor nach einem FRU-Austausch der Computer wieder angeschlossen wird, muß sichergestellt werden, daß keine Schrauben, Federn oder andere Kleinteile fehlen oder im Gehäuse vergessen wurden. Der Computer muß geschüttelt und auf Klappergeräusche geprüft werden. Metallteile oder-splitter können Kurzschlüsse erzeugen.



#### VORSICHT

Die Bereitschaftsbatterie, die sich unter dem Diskettenlaufwerk befindet, kann geringe Mengen Nickel und Cadmium enthalten. Sie darf nur durch die Verkaufsstelle oder den IBM Kundendienst ausgetauscht werden. Sie darf nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Die Batterie kann schwere Verbrennungen oder Verätzungen verursachen. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Bereitschafts-oder Systembatterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.



#### VORSICHT

Akkus enthalten geringe Mengen von Nickel. Sie dürfen nicht zerlegt, wiederaufgeladen, kurzgeschlossen, oder Feuer oder Wasser ausgesetzt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.



#### **VORSICHT**

Die Systembatterie ist eine Lithiumbatterie. Sie kann sich entzünden, explodieren oder schwere Verbrennungen hervorrufen. Batterien dieses Typs dürfen nicht aufgeladen, zerlegt, über 100°C erhitzt oder verbrannt werden. Auch darf ihr Inhalt nicht mit Wasser in Verbindung gebracht oder der zur richtigen Polung angebrachte Verbindungsstecker entfernt werden. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Beim Ersetzen der Batterie nur Batterien des Typs verwenden, der in der Ersatzteilliste aufgeführt ist. Der Einsatz falscher Batterien kann zu Entzündung oder Explosion führen.



#### **VORSICHT**

Die Leuchtstoffröhre im LCD-Bildschirm enthält Quecksilber. Bei der Entsorgung die örtlichen Bestimmungen für Sondermüll beachten. Der LCD-Bildschirm besteht aus Glas und kann zerbrechen, wenn er unsachgemäß behandelt wird oder der Computer auf den Boden fällt. Wenn der Bildschirm beschädigt ist und die darin befindliche Flüssigkeit in Kontakt mit Haut und Augen gerät, sollten die betroffenen Stellen mindestens 15 Minuten mit Wasser abgespült und bei Beschwerden anschließend ein Arzt aufgesucht werden.



#### VORSICHT

Aus Sicherheitsgründen die Kunststoffabdeckung, die den unteren Teil der Spannungswandlerplatine umgibt, nicht entfernen.



#### **VORSICHT**

Obwohl Hauptbatterien eine niedrige Spannung haben, können sie doch bei Kurzschluß oder Erdung genug Strom abgeben, um brennbare Materialien zu entzünden oder Verletzungen bei Personen hervorzurufen.



#### **VORSICHT**

Wenn ein Austausch der FRU bei laufendem Betrieb nicht erlaubt ist, gehen Sie beim Austausch der FRU wie folgt vor: Schalten Sie den Computer aus, ziehen Sie alle Netzkabel von den Netzsteckdosen ab, entfernen Sie den Akku und ziehen Sie alle miteinander verbundenen Kabel ab.



סכנה

לפני חפעלת חמחשב לאחר תחלפת FRU יש לוודא שכל תברגים, חקפיצים, וחלקים קטנים אחרים נמצאים במקומם ואינם חופשיים לזוז בתוך חמחשב. כדי לוודא זאת, יש לטלטל את חמחשב ולחקשיב לגילוי קולות שקשוק. חלקי או שבבי מתכת עלולים לגרום לקצרים חשמליים.



סכנה

סוללות חמתנת מסוימות מכילות כמות קטנת של ניקל וקדמיום. אין לפרק סוללת חמתנה, לטעון אותה מחדש, להשליך אותה לאש או למים או לקצר אותה. יש לסלק את הסוללה כנדרש על ידי התקנות והחוקים המקומיים. יש להשתמש רק בסוללה המופיעה ברשימת החלקים המתאימה. שימוש בסוללה לא מתאימה עלול לגרום להצתה או התפוצצות של הסוללה.



סכנה

מארז הסוללה מכיל כמות קטנה של ניקל וקדמיום. אין לפרק את מארז הסוללה, להשליך אותו לאש או למים או לקצר אותו. יש לסלק את מארז הסוללה הסוללה כנדרש על ידי התקנות והחוקים המקומיים. יש להשתמש רק בסוללה המופיעה ברשימת החלקים המתאימה בזמן החלפת מארז הסוללה. שימוש בסוללה לא מתאימה עלול לגרום להצתה או התפוצצות של הסוללה.



מכנה

סוללת חליתיום עלולה לגרום לשריפה, להתפוצצות או לכוויות קשות. אין לטעון אותה מחדש, לסלק את המחבר המקוטב שלה, לפרק אותה או לחמם אותה לסמפרטורה העולה על 100 מעלות צלויוס. אין לשרוף את הסוללה ואין לחשוף את תוכן התא למים. יש לסלק את הסוללה כנדני בתקנות ובחוקים המקומיים. יש להשתמש רק בסוללה המופיעה ברשימת החלקים המתאימים. שימוש בסוללה אחרת עלול לגרום לסכנת שריפה או התפוצצות.



סכנה

אם מסך הגביש הנוזלי (LCD) נשבר והנוזל מתוך המסך בא במגע עם עיניכם או ידיכם, שטפו את האזורים הנגועים מיד במים במשך 15 דקות לפחות. פנו לקבלת עזרה רפואית אם תסמינים הנובעים מהמגע עם הנוזל נמשכים לאחר השטיפה.



סכנה

כדי למנוע התחשמלות, אין לחסיר את מכסה הפלסטיק המגן על חלקו התחתון של הכרטיס החפוך.



סכנה

אף שהסוללות הראשיות הן בעלות מתח נמוך, סוללה מקוצרת או מוארקת עלולה להפיק זרם מספיק לגרימת כוויות או להצתת חומרים דליקים.



סכנה

אלא אם כן מותרת יחחלפה חמהי של ה-FRU המוחלף, פעלו כדילחלן לפני הסרתו: כבו את המחשב, נתקו את כל כבלי החשמל מחשקעים, הוציאו את מארז הסוללות ונתקו את כל הכבלים המחוברים.



危険

FRU の交換後、 ThinkPad の電源を入れる前に、ねじ、バネ、その他の小さな部 品がすべて正しい位置にあり、また ThinkPad の内部で緩んでいないことを確認し てください。

これを確認するには、 ThinkPad を振って、カチャカチャと音がしないか確かめます。 金属部品や金属破片はショートの原因になることがあります。



危険

予備バッテリーの中には少量のニッケルとカドミウムが含まれているものがあります。したがって、予備バッテリーの分解、再充電、火または水の中への投棄、またはショートさせることは決して行わないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。



危険

バッテリー・パックには少量のニッケルが含まれています。バッテリー・パックを分解したり、火または水の中に投げ込んだり、ショートさせないでください。バッテリー・パックの廃棄にあたっては、地方自治体の条例または規則に従ってください。バッテリー・パックを交換するときは、適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。



合隘

リチウム・バッテリーは、火災、爆発、または重症のやけどを引き起こすことがあります。バックアップ・バッテリーの充電、その極性コネクターの取り外し、バッテリー本体の分解、100℃(212°F)以上への加熱、焼却、電池の中身を水に浸すことはしないでください。バッテリーを廃棄する場合は地方自治体の条例に従ってください。適切なパーツ・リストにあるバッテリーだけを使用してください。誤ったバッテリーを使用すると、バッテリーが発火したり、爆発したりすることがあります。



危険

LCD が破損し、LCD の中の液体が目に入ったり、手に触れたりした場合は、液体が触れた部分を少なくとも15分間洗い流してください。洗い流した後に、液体によって何らかの症状が現れた場合は、医師の治療を受けてください。



危険

感電を防ぐため、インバーター・カードの下部を保護しているプラスチック・カ バーを外さないでください。



危険

メイン・バッテリーの電圧は低くても、ショートしたり、接地したバッテリーが、作業者にやけどを負わせたり、可燃物を燃やすだけの電流を発生させる場合があります。



危険

交換しようとしている FRU がホット・スワップに対応していない場合、それを取り外す前に、コンピューターの電源をオフにし、すべての電源コードをコンセントから抜き、バッテリー・パックを取り外して、相互接続しているケーブルをすべて切り離してください。



위험

FRU를 교체하고 나서 컴퓨터 전원을 켜기 전에 모든 나사, 스프링 및 기타 작은 부품들이 올바른 위치에 있는지, 컴퓨터 내부에 단단하게 연결되어 있 는지 확인하십시오. 컴퓨터를 흔들어 달깍거리는 소리가 나지 않는지 확인하 십시오. 금속 부품 또는 금속 조각은 누전을 일으킬 수 있습니다.



위호

일부 보조 배터리에는 소량의 니켈 및 카트뮴이 포함되어 있습니다. 보조 배터리를 분해하거나, 다시 충전하거나, 불 또는 물에 던지거나, 단락시키지 마십시오. 배터리 팩을 폐기할 때에는 해당 지역의 법률 규정을 따르십시오. 배터리 팩을 교체할 때에는 올바른 배터리만 사용하십시오. 올바르지 않은 배터리를 사용하면 배터리가 발화되거나 폭발할 수 있습니다.



위험

배터리 팩에는 소량의 니켈이 포함되어 있습니다. 배터리 팩을 분해하거나, 불 또는 물에 던지거나, 단락시키지 마십시오. 배터리 팩을 폐기할 때에는 해 당 지역의 법률 규정을 따르십시오. 배터리 팩을 교체할 때에는 올바른 배터 리만 사용하십시오. 올바르지 않은 배터리를 사용하면 배터리가 발화되거나 폭발할 수 있습니다.



의하

리튬 배터리는 화재, 폭발 또는 심각한 화상을 일으킬 수 있습니다. 리튬 배터리를 다시 충전하거나, 극성 커넥터를 제거하거나, 분해하거나, 100C(212F)이상으로 가열하거나, 소각하거나, 전지 내용물을 물에 노출시키지 마십시오. 배터리를 폐기할 때에는 해당 지역을 법률 규정을 따르십시오. 올바른 배터리만 사용하십시오. 올바르지 않은 배터리를 사용하면 배터리가 발화되거나 폭발할 수 있습니다.



위헌

LCD가 파손되어 LCD 내부의 액체가 눈에 들어가거나 손에 묻으면 즉시 깨끗한 물로 15분 이상 닦아 내십시오. 썻은 후에 조금이라도 이상을 느끼면 즉시 병원에 가서 의사의 진찰을 받아야 합니다.



위호

전기적 위험을 방지하려면 인버터 카드의 아래 부분을 보호하는 플라스틱 덮개를 제거하지 마십시오.



위호

기본 배터리의 전압은 낮지만, 단락되거나 접지된 배터리는 화상을 입히기에 충분한 전류와 가연성 물질을 발생시킬 수 있습니다.



위현

FRU 교체 시 Hot Swap이 지원되지 않는 경우, FRU를 제거하기 전에 컴퓨터의 전원을 끄고, 전기 콘센트에서 전원 코드를 분리하고, 배터리를 제거한 후, 연결된 모든 케이블을 분리하십시오.



**PELIGRO** 

Antes de encender el sistema despues de sustituir una FRU, compruebe que todos los tornillos, muelles y demás piezas pequeñas se encuentran en su sitio y no se encuentran sueltas dentro del sistema. Compruébelo agitando el sistema y escuchando los posibles ruidos que provocarían. Las piezas metálicas pueden causar cortocircuitos eléctricos.



**PELIGRO** 

Algunas baterías de reserva contienen una pequeña cantidad de níquel y cadmio. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.



**PELIGRO** 

Las baterías contienen pequeñas cantidades de níquel. No las desmonte, ni recargue, ni las eche al fuego o al agua ni las cortocircuite. Deséchelas tal como dispone la normativa local. Utilice sólo baterías que se encuentren en la lista de piezas al sustituir la batería. La utilización de una batería no apropiada puede provocar la ignición o explosión de la misma.



**PELIGRO** 

La batería de repuesto es una batería de litio y puede provocar incendios, explosiones o quemaduras graves. No la recargue, ni quite el conector polarizado, ni la desmonte, ni caliente por encima de los 100°C (212°F), ni la incinere ni exponga el contenido de sus celdas al agua. Deséchela tal como dispone la normativa local.



PELIGRO

Si la LCD se rompe y el fluido de su interior entra en contacto con sus ojos o sus manos, lave inmediatamente las áreas afectadas con agua durante 15 minutos como mínimo. Obtenga atención medica si se presenta algún síntoma del fluido despues de lavarse.



**PELIGRO** 

Para evitar descargas, no quite la cubierta de plástico que rodea la parte baja de la tarjeta invertida.



**PELIGRO** 

Aunque las baterías principales tienen un voltaje bajo, una batería cortocircuitada o con contacto a tierra puede producir la corriente suficiente como para quemar material combustible o provocar quemaduras en el personal.



**PELIGRO** 

Salvo que se permita el intercambio en caliente para la unidad sustituible localmente, realice lo siguiente antes de extraerla: apague el sistema, desconecte todos los cables de alimentación de las tomas de alimentación eléctrica, extraiga la batería y desconecte los cables de interconexión.



危險

完成 FRU 更換之後,在開啟電腦的電源之前,請確定所有螺絲、彈簧及其他小零件都已歸位,沒有遺留在電腦內部。 若要確認這一點,請搖晃電腦,聽聽看是否有卡嗒的聲響。 金屬零件或儀錶的火花會造成電線短路。



危險

部分備用電池含有微量的鎳和鎘。請勿拆開備用電池、再充電、丟入火或水中, 或使其形成短路。請按照當地法令或規定來棄置電池。

僅限使用零件清單中的電池。使用不適當的電池會導致電池起火或爆炸。



危險

電池套件含有微量的鎳。請勿拆開電池套件、丟入火或水中,或使其形成短路。請按照當地法令或規定來棄置電池套件。

更換電池套件時,僅限使用零件清單中的電池。使用不適當的電池會導致電池起火或爆炸。



危險

鋰電池會導致起火、爆炸或嚴重燒傷。請勿再充電、拔除其電極接頭、拆開、加熱超過  $100^{\circ}$ C  $(212^{\circ}F)$ 、焚燒,或讓電池組成物浸到水。請按照當地法令或規定來棄置電池。

僅限使用零件清單中的電池。使用不適當的電池會導致電池起火或爆炸。



危險

如果 LCD 破裂導致 LCD 流出的液體沾到您的眼睛或手,請立即以清水沖洗沾染部位至少 15 分鐘。如果在清洗後出現該液體所造成的任何症狀,請就醫治療。



危險

為避免電擊,請勿拆下轉換卡下面的塑膠護蓋。



雖然主電池的電壓很低,但短路或接地電池所產生的電流,仍足以使人燒傷或 使可燃物質起火。



除非 FRU 允許以熱抽換來替換,否則請依下列方式將其移除:將電腦關機,拔除插座上所有電源線,移除電池包,並拔開任何交互連接的線材。

# Chapter 2. General checkout

This chapter contains the following topics:

Before you go to the checkout instructions, ensure that you read the following important notes.

#### Important notes:

- . Only certified trained personnel should service the Chromebook.
- . Before replacing any FRU, read the entire page on removing and replacing FRUs.
- Be extremely careful during such writing operations as copying, saving, or formatting. Drives in the Chromebook that you are servicing sequence might have been altered. If you select an incorrect drive, data or programs might be overwritten.
- Replace a FRU only with another FRU of the correct model. When you replace a FRU, make sure that the model of the machine and the FRU part number are correct by referring to the FRU parts list.
- A FRU should not be replaced because of a single, unreproducible failure. Single failures can occur for a variety of reasons that have nothing to do with a hardware defect, such as cosmic radiation, electrostatic discharge, or software errors. Consider replacing a FRU only when a problem recurs. If you suspect that a FRU is defective, clear the error log and run the test again. If the error does not recur, do not replace the FRU.
- · Be careful not to replace a nondefective FRU.

### What to do first

When you return a FRU, you must include the following information in the parts exchange form or parts return form that you attach to it:

- 1. Name and phone number of service technician
- 2. Date of service
- 3. Date on which the machine failed
- 4. Date of purchase
- 5. Failure symptoms, error codes appearing on the display, and beep symptoms
- 6. Procedure index and page number in which the failing FRU was detected
- 7. Failing FRU name and part number
- 8. Machine type, model number, and serial number
- 9. Customer's name and address

**Note:** During the warranty period, the customer may be responsible for repair costs if the Chromebook damage was caused by misuse, accident, modification, unsuitable physical or operating environment, or improper maintenance by the customer. Following is a list of some common items that are not covered under warranty and some symptoms that might indicate that the system was subjected to stress beyond normal use.

Before checking problems with the Chromebook, determine whether the damage is covered under the warranty by referring to the following list:

#### The following are not covered under warranty:

- LCD panel cracked from the application of excessive force or from being dropped
- Scratched (cosmetic) parts
- Distortion, deformation, or discoloration of the cosmetic parts
- Plastic parts, latches, pins, or connectors that have been cracked or broken by excessive force

© Copyright Lenovo 2024 21

- Damage caused by liquid spilled into the system
- Damage caused by the improper insertion of a personal-computer card (PC card) or the installation of an incompatible card
- Improper disc insertion or use of an external optical drive
- Fuses blown by attachment of a non-supported device
- Forgotten Chromebook password (making the Chromebook unusable)
- · Sticky keys caused by spilling a liquid onto the keyboard
- Use of an incorrect ac power adapter on laptop products

#### The following symptoms might indicate damage caused by non-warranted activities:

- Missing parts might be a symptom of unauthorized service or modification.
- Check for obvious damage to a hard disk drive. If the spindle of a hard disk drive becomes noisy, the hard disk drive might have been dropped or subject to excessive force.

### **CRU list**

Table 1. Model: LNV CB Duet 11M889 (Machine type: 83HH)

| CRU                        | Туре         |
|----------------------------|--------------|
| ac power adapter           | self-service |
| Folio keyboard*            | self-service |
| Kickstand*                 | self-service |
| Lenovo USI Pen 2 Magnetic* | self-service |
| Power cord                 | self-service |

Table 2. Model: LNV Chrome Duet EDU G2 (Machine type: 83HJ, 83HK)

| CRU                        | Туре         |
|----------------------------|--------------|
| ac power adapter           | self-service |
| Folio keyboard*            | self-service |
| Lenovo USI Pen 2 Magnetic* | self-service |
| Power cord                 | self-service |

<sup>\*</sup> for selected models

# Chapter 3. Create and use a USB repair shim

### What is a USB repair shim?

You can create a USB repair shim by writing a repair shim image to a USB storage drive. With the USB repair shim, you can:

- Refresh the Chromebook system with the latest firmware.
- Diagnose problems and restore the system to factory settings.

**Note:** Before replacing any FRUs, use the USB repair shim to diagnose and identify problems.

When you use the USB repair shim to diagnose problems, the Chromebook enters the factory-test-image environment and runs through factory test items.

**Note:** For the latest and detailed shim instruction, you can refer to the RMA Shim SOP from "Drivers & Software" on <a href="https://support.lenovo.com">https://support.lenovo.com</a> with Lenovo service credential.

We strongly recommend that only trained technicians install the motherboard and shim. Customers undertake self-repair at their own risk. If customer requests the Self Repair Shim, please call Lenovo Customer Support Center. Go to <a href="https://pcsupport.lenovo.com/supportphonelist">https://pcsupport.lenovo.com/supportphonelist</a> for the latest phone numbers.

# **Chapter 4. Identifying FRUs (CRUs)**

# **Locate FRUs and CRUs**

The exploded illustrations help Lenovo service technicians identify FRUs or CRUs that they may need to replace when servicing a customer's Chromebook.




Figure 1. Exploded view

Table 3. FRU (CRU) categories

| No. | FRU (CRU) category                     |
|-----|--|
| 0   | Kickstand (for LNV CB Duet 11M889)*    |
| 2   | Microphone cables                      |
| 3   | Rear-facing camera bracket             |
| 4   | Rear-facing camera                     |
| 5   | Front-facing camera                    |
| 6   | Camera cover                           |
| 7   | Camera cover bracket                   |
| 8   | Camera mylar                           |
| 9   | LCD and system board mylar             |
| 10  | System board                           |
| m   | System board USB Type-C bracket        |
| 12  | System board USB Type-C mylar          |
| 13  | I/O board                              |
| 14  | I/O board USB Type-C bracket           |
| 15  | USB Type-C cable                       |
| 16  | Power and volume board cable           |
| 17  | Audio cable                            |
| 18  | Power and volume board                 |
| 19  | Speakers                               |
| 20  | Folio keyboard*                        |
| 21  | Pogo pin cable                         |
| 22  | Pogo pin bracket                       |
| 23  | LCD cover                              |
| 24  | Battery pack                           |
| 25  | Battery pack rubber                    |
| 26  | Battery cable mylar                    |
| 27  | Battery cable bracket                  |
| 28  | Antenna module                         |
| 29  | Antenna cable mylar                    |
| 30  | EDP cable                              |
| 31  | Removable tapes                        |
| 32  | LCD module                             |
| 33  | Camera LED cable                       |
| 34  | Kickstand (for LNV Chrome Duet EDU G2) |

Table 3. FRU (CRU) categories (continued)

| a | ac power adapter           |
|---|----------------------------|
| b | Power cord                 |
| C | Lenovo USI Pen 2 Magnetic* |
| d | Screw kit                  |

<sup>\*</sup> for selected models

# Chapter 5. Removing a FRU or CRU

### **Service tools**

The following table lists tools for servicing Lenovo Chromebooks. Tools with a cross mark are needed for serving the product models as described by this publication. Prepare them before you service the product.

Table 4. Service tools

| Service tool and consumable            | Model applicability            |
|--|--------------------------------|
| Screw driver (Phillips head) (PH1/PH0) | X                              |
| Screw driver (Torx head) (T5)          | X (for LNV Chrome Duet EDU G2) |
| Screw driver (Torx head) (T30)         |                                |
| Pry tool 1                             | X                              |
| Tweezers (conductive)                  | X                              |
| Tweezers (isolated)                    |                                |
| Suction cup                            |                                |
| Hexagonal socket                       |                                |
| Thermal interface materials            | X                              |
| Acetate tape                           | X                              |
| Polyamide tape                         |                                |
| Mylar tape                             |                                |
| Electrical tape                        |                                |
| Double-sided tape                      |                                |
| Conductive tape                        |                                |
| Eraser                                 |                                |
| Heat gun                               |                                |
| Brown brush                            |                                |

#### Notes:

- T30 screw drivers are used to service the new Intel Xeon CPUs.
- Hexagonal sockets are used to remove antenna connectors.

# **General guidelines**

When removing or replacing a FRU, ensure that you observe the following general guidelines:

- 1. Do not try to service any Chromebook unless you have been trained and certified. An untrained person runs the risk of damaging parts.
- Begin by removing any FRUs that have to be removed before replacing the failing FRU. Any such FRUs are listed at the beginning of each FRU replacement procedure. Remove them in the order in which they are listed.

- 3. Follow the correct sequence in the steps for removing a FRU, as shown in the illustrations by the numbers in square callouts.
- 4. When removing a FRU, move it in the direction as shown by the arrow in the illustration.
- 5. To install a new FRU in place, perform the removal procedure in reverse and follow any notes that pertain to replacement.
- 6. When replacing a FRU, carefully retain and reuse all screws.
- 7. When replacing the base cover, reapply all labels that come with the replacement base cover. If some original labels are not included with the replacement base cover, peel them off from the original base cover and paste them on the replacement base cover.



Before removing any FRU or CRU, shut down the Chromebook and unplug all power cords from electrical outlets.

Attention: After replacing a FRU, do not turn on the Chromebook until you have ensured that all screws, springs, and other small parts are in place and none are loose inside the Chromebook. Verify this by shaking the Chromebook gently and listening for rattling sounds. Metallic parts or metal flakes can cause electrical short circuits.

Attention: The system board is sensitive to and can be damaged by ESD. Before touching it, establish personal grounding by touching a ground point with one hand or by using an ESD strap (P/N 6405959).

### Remove the kickstand (for LNV Chrome Duet EDU G2)

Make sure the Chromebook has been shut down before servicing the Chromebook.

- Step 1. Place the Chromebook upside down on a flat surface.
- Step 2. Remove three screws and then remove the kickstand.




Figure 2. Remove three screws and then remove the kickstand

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.6 × L5.0          | 3                | 1.2 ± 0.15            |

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement part:

Kickstand (for LNV Chrome Duet EDU G2)

#### Remove the LCD module

Make sure the following FRUs (or CRUs) have been removed.

"Remove the kickstand (for LNV Chrome Duet EDU G2)" on page 30

- Step 1. Place the Chromebook on a flat surface.
- Step 2. Insert the pry tool at the location marked with callout **1** and then loosen the hooks in sequence.
- Step 3. Lift the LCD module.




Figure 3. Lift the LCD module

Peel off the mylar and disconnect the EDP cable from the system board. Then, remove the LCD Step 4. module.

**Attention:** Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 4. Remove the LCD module

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

LCD module

LCD and system board mylar

#### Remove the EDP cable

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Peel off the mylar and then disconnect and remove the EDP cable.

Attention: Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 5. Disconnect and remove the EDP cable

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement parts:

EDP cable

LCD and system board mylar

#### Remove the battery pack

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Remove one screw and then remove the battery cable bracket.



Figure 6. Remove one screw and the battery cable bracket

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.6 × L1.7          | 1                | 1.2 ± 0.15            |

Step 2. Disconnect the battery cable and remove the battery pack rubber. Then, pull out the removable tapes and remove the battery pack.

For Chromebooks with two strips of removable tapes:




Figure 7. Disconnect the battery cable and remove the battery pack rubber, tapes, and battery pack

#### For Chromebooks with four strips of removable tapes:




Figure 8. Disconnect the battery cable and remove the battery pack rubber, tapes, and battery pack

#### Notes:

- When pulling the removable tapes, pull it at an angle rather than straight upward.
- Removable tapes are not reusable. Use new removable tapes when the battery pack is reinstalled or replaced.
- When reinstalling the new removable tapes, ensure that the tapes are properly installed within the specified areas marked 1, 2, 3, and 4.




Figure 9. Install the removable tapes within specified areas

• When reinstalling the new removable tape to the area 2 without marking lines, ensure that the tape does not cover the laser-engraved areas marked a and or the pogo pin cable marked c.



Figure 10. Install the removable tapes without covering specified areas and cable

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

Battery cable bracket

Battery pack

Battery pack rubber

Removable tape

#### Remove the pogo pin bracket

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the battery pack" on page 33

Step 1. Remove four screws and then remove the pogo pin bracket.




Figure 11. Remove four screws and remove the pogo pin bracket

| Screw specifications Number of screws |   | Torque force (kgf.cm) |  |
|---------------------------------------|---|-----------------------|--|
| M1.4 × L2.5                           | 4 | 0.5 ± 0.15            |  |

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

Pogo pin bracket

## Remove the pogo pin cable

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the battery pack" on page 33

"Remove the pogo pin bracket" on page 36

Step 1. Disconnect the pogo pin cable from the system board and then remove the pogo pin cable.

Attention: Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 12. Disconnect and remove the pogo pin cable

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

Pogo pin cable

## Remove the system board USB Type-C mylar

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Disconnect the battery cable and then remove the system board USB Type-C mylar.




Figure 13. Disconnect the battery cable and remove the system board USB Type-C mylar

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement part:

System board USB Type-C mylar

### Remove the system board USB Type-C bracket

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the system board USB Type-C mylar" on page 37

Step 1. Remove two screws and then remove the system board USB Type-C bracket.

Attention: Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 14. Remove two screws and the system board USB Type-C bracket

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.6 × L1.7          | 2                | 1.2 ± 0.15            |

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

System board USB Type-C bracket

## Remove the speakers

Make sure the following FRUs (CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the system board USB Type-C mylar" on page 37

Step 1. Peel back the mylar.



Figure 15. Peel back the mylar

Step 2. Disconnect the left and right speaker cables from the system board, remove six screws, and remove the speakers.

**Attention:** Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 16. Disconnect and remove the speakers

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.4 × L2.5          | 6                | 0.5 ± 0.15            |

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

Speakers

#### Remove the antenna module

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the battery pack" on page 33

Step 1. Disconnect the USB Type-C cable and pogo pin cable from the system board and then remove the antenna cable mylar.

Attention: Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 17. Disconnect the USB Type-C cable and pogo pin cable and remove the antenna cable mylar

Step 2. Disconnect the antenna cables from the system board, remove the antenna cables from the cable guide, and then remove the antenna module.




Figure 18. Remove the antennas and the antenna module

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement parts:

Antenna cable mylar

Antenna module

#### Remove the I/O board bracket

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Disconnect the battery cable, remove two screws, and remove the I/O board bracket.




Figure 19. Disconnect the battery cable, remove two screws and the I/O board bracket

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.6 × L1.7          | 2                | 1.2 ± 0.15            |

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement part:

I/O board bracket

#### Remove the I/O board

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the I/O board bracket" on page 41

Step 1. Peel off the mylar.



Figure 20. Peel off the mylar

Step 2. Disconnect the USB Type-C cable and the audio cable from the system board.




Figure 21. Disconnect the USB Type-C cable and the audio cable

Step 3. Remove the I/O board.



Figure 22. Remove the I/O board

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

I/O board

## Remove the USB Type-C cable and audio cable

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the battery pack" on page 33

Step 1. Peel off the mylar.




Figure 23. Peel off the mylar

Disconnect the USB Type-C cable and audio cable from the I/O board and the system board and Step 2. then remove the USB Type-C cable and audio cable.




Figure 24. Disconnect and remove the USB Type-C cable and audio cable

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

Audio cable USB Type-C cable

#### Remove the power and volume board and cable

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Disconnect the battery cable and then peel off the mylar.




Figure 25. Disconnect the battery cable and peel off the mylar

Step 2. Disconnect and remove the power and volume board cable.



Figure 26. Disconnect and remove the power and volume board cable

#### Step 3. Remove the power and volume board.



Figure 27. Remove the power and volume board

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

Power and volume board

Power and volume board cable

### Remove the camera cover, camera cover bracket, camera LED cable, and front-facing camera

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Disconnect the battery cable and then disconnect the front-facing camera cable and camera LED cable from the system board.




Figure 28. Disconnect the battery cable, camera, and camera LED cable

Step 2. Remove two screws and then remove the camera cover bracket.




Figure 29. Remove two screws and the camera cover bracket

| Screw specifications | Number of screws | Torque force (kgf.cm) |
|----------------------|------------------|-----------------------|
| M1.4 × L2.5          | 2                | $0.5 \pm 0.15$        |

Step 3. Remove the camera cover.



Figure 30. Remove the camera cover

Step 4. Remove the camera LED cable and then remove the front-facing camera.




Figure 31. Remove the camera LED cable and the front-facing camera

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement parts:

Camera cover

Camera cover bracket

Camera LED cable

Front-facing camera

## Remove the microphone cables

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the camera cover, camera cover bracket, camera LED cable, and front-facing camera" on page 45

Step 1. Disconnect the microphone cables from the system board and then remove the microphone cables.

Attention: Use your fingernail to pull the connector to unplug it. Do not pull the cable.




Figure 32. Disconnect and remove the microphone cables

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

Microphone cable

## Remove the rear-facing camera bracket

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

Step 1. Disconnect the battery cable, remove two screws, and then remove the rear-facing camera bracket.




Figure 33. Disconnect the battery cable, remove two screws, and the rear-facing camera bracket

| Screw specifications Number of screws |   | Torque force (kgf.cm) |  |
|---------------------------------------|---|-----------------------|--|
| M1.4 × L2.5                           | 2 | $0.5 \pm 0.15$        |  |

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

Rear-facing camera bracket

## Remove the rear-facing camera

Make sure the following FRUs (or CRUs) have been removed.

"Remove the kickstand (for LNV Chrome Duet EDU G2)" on page 30

"Remove the rear-facing camera bracket" on page 48

Step 1. Disconnect the rear-facing camera cable from the system board, and then remove the rear-facing camera.



Figure 34. Disconnect and remove the rear-facing camera

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

Rear-facing camera

#### Remove the system board

Make sure the following FRUs (or CRUs) have been removed.

"Remove the LCD module" on page 31

"Remove the system board USB Type-C mylar" on page 37

"Remove the system board USB Type-C bracket" on page 38

Step 1. Disconnect cable connectors from the system board.




Figure 35. Disconnect cables

Step 2. Remove five screws and then remove the system board.




Figure 36. Remove five screws and the system board

| Screw specifications | rew specifications Number of screws |            |
|----------------------|-------------------------------------|------------|
| M1.6 × L1.7          | 5                                   | 1.2 ± 0.15 |

Go to https://support.lenovo.com/partslookup to look up the Lenovo part numbers of the following replacement part:

System board

#### Remove the LCD cover

Make sure the following FRUs (CRUs) have been removed.

- "Remove the kickstand (for LNV Chrome Duet EDU G2)" on page 30
- "Remove the LCD module" on page 31
- "Remove the EDP cable" on page 32
- "Remove the battery pack" on page 33
- "Remove the pogo pin bracket" on page 36
- "Remove the pogo pin cable" on page 36
- "Remove the system board USB Type-C mylar" on page 37
- "Remove the system board USB Type-C bracket" on page 38
- "Remove the speakers" on page 38
- "Remove the antenna module" on page 40
- "Remove the I/O board bracket" on page 41
- "Remove the I/O board" on page 41
- "Remove the USB Type-C cable and audio cable" on page 43
- "Remove the power and volume board and cable" on page 44
- "Remove the camera cover, camera cover bracket, camera LED cable, and front-facing camera" on page 45
- "Remove the microphone cables" on page 47

Go to <a href="https://support.lenovo.com/partslookup">https://support.lenovo.com/partslookup</a> to look up the Lenovo part numbers of the following replacement part:

LCD cover

<sup>&</sup>quot;Remove the rear-facing camera bracket" on page 48

<sup>&</sup>quot;Remove the rear-facing camera" on page 49

<sup>&</sup>quot;Remove the system board" on page 50

## **Chapter 6. Label locations**




Figure 37. Label layout on the back side of the base cover (for LNV CB Duet 11M889)




Figure 38. Label layout on the back side of the kickstand (for LNV Chrome Duet EDU G2)

Labels attached to the base cover are country/region specific. Make sure to apply the appropriate labels to the replacement base cover.

Table 5. All base cover labels

| Label | Label name            | Applied country/region Label dimensions |               |
|-------|-----------------------|---|---------------|
| 1     | Indonesia SDPPI label | Indonesia                               | 40 mm × 10 mm |

© Copyright Lenovo 2024 53

Table 5. All base cover labels (continued)

| 2 | CO2 offset service label | All | 18 mm × 18 mm   |
|---|--------------------------|-----|-----------------|
| 3 | Energy star label        | All | 11 mm × 11 mm   |
| 4 | Microprocessor label     | All | 18 mm × 18 mm   |
| 5 | QR code Label            | All | 17 mm × 26.1 mm |
| 6 | Rating label             | All | 100 mm × 30 mm  |
| 7 | Asset label              | All | 101 mm × 50 mm  |

## **Trademarks**

LENOVO and the LENOVO logo are trademarks of Lenovo.

All other trademarks are the property of their respective owners. © 2024 Lenovo.

# Lenovo