

# Statement of Volatility – Dell Pro Thunderbolt 4 Dock WD25TB4

⚠ CAUTION: A CAUTION indicates either potential damage to hardware or erasure of data and tells you how to avoid the problem.

The Dell Pro Thunderbolt 4 Dock WD25TB4 contains both volatile and non-volatile components. Volatile components erase their data immediately after power is removed from the component. Non-volatile components continue to retain their data even after power is removed from the component. The following non-volatile components are present in the Dell Pro Thunderbolt 4 Dock WD25TB4.

**Table 1. List of non-volatile components on system board**

Description	Reference designator	Volatility description	User accessible for external data	Remedial action (action necessary to erase data)
Thunderbolt 4 SPI ROM	UT71	Non-Volatile memory size 32 Mbit, stores Thunderbolt4 Goshen Ridge FW	No	Not applicable
USB2 hub SPI ROM	UU34	Non-Volatile memory size 32 Mbit, stores Parade USB2 hub FW	No	Not applicable
MST hub SPI ROM	UV18	Non-Volatile memory size 8 Mbit, stores MST(DP) hub FW	No	Not applicable
USB3 Gen2 hub SPI ROM	UU29	Non-Volatile memory size 4 Mbit, stores USB3 Gen2 hub FW	No	Not applicable
USB3 Gen2 hub SPI ROM	UU31	Non-Volatile memory size 4 Mbit, stores USB3 Gen2 hub FW	No	Not applicable
Intel vPro LAN SPI ROM	UL6	Non-Volatile memory size 16 Mbit, stores Intel vPro LAN i226 FW	No	Not applicable
DMC (or Dock EC)	UE1	Non-Volatile memory Flash, Store EC program code to control <b>GPIO</b> and communication with many devices of dock using i2C interface	No	Not applicable
Security IC	UE17	Non-Volatile memory, stores Security FW	No	Not applicable
UFP PD	UP5	Non-Volatile memory, stores UFP PD FW	No	Not applicable
DFP PD	UP15	Non-Volatile memory, stores DFP PD FW	No	Not applicable
DFP PD	UP17	Non-Volatile memory, stores DFP PD FW	No	Not applicable

⚠ CAUTION: All other components on the system board erase data if power is removed from the docking station.

© 2025 Dell Inc. or its subsidiaries. All Rights Reserved. Dell Technologies, Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

2025-04