

# SR-100 DIN Rail Media Converters

## Fast Ethernet Copper to Fiber Converters



- 100Base-TX to 100Base-X Fiber Media Converters
- Link copper to multimode or single mode fiber
- Dual or Single fiber ST/SC connectors
- Extend network distances up to 120km
- Advanced Features: Link Pass-Through, Far-End Fault, Auto-MDIX
- Triple Power Input: Dual Terminal block power connector & T-Bus

Perle **SR-100 DIN Rail Media Converters** transparently connect UTP copper to fiber. These Fast Ethernet Media Converters provide an economical path to:

- extend the distance of an existing network by linking CAT5/6/7 cabling to multimode or single mode fiber
- extend the life of non-fiber based equipment by enabling data transmission from 100Base-TX devices over fiber
- extend the distance between two copper-based devices or networks
- protect Ethernet data from EMI noise and interference by inter-connecting your copper-Ethernet devices over fiber in industrial plants.

Some SR-100 Media Converters are also available with **an SFP slot** or support for **-40C to +75C (-40F to +167F) extended operating temperatures**.

Network Administrators can rest assured with Perle's advanced features such as Auto-Negotiation, Auto-MDIX, Link Pass-Through, Far End Fault, and Pause which make the end to end link completely transparent. This allows for more efficient troubleshooting and less on-site maintenance. These cost and time saving features, along with a lifetime warranty and free worldwide technical support, make **SR-100 Fast Ethernet Media Converters** the smart choice for IT professionals.

## SR-100 Fiber Media Converter Features: 100Base-TX to 100Base-X

---

### DIN Rail Enclosure

Easily mount on a DIN rail or inside distribution boxes using native DIN Rail enclosure with grounding clip. No need for add-on brackets.

---

### Auto-Negotiation

The media converter supports auto negotiation on the fast ethernet 100Base-TX interface.

---

---

## Auto-MDIX

---

Auto-MDIX (automatic medium-dependant interface crossover) detects the signaling on the 100Base-TX interface to determine the type of cable connected (straight-through or crossover) and automatically configures the connection when enabled. With Auto-MDIX enabled, either a straight-through or crossover type cable can be used to connect the media converter to the device on the other end of the cable.

---

## Link Pass-Through

---

With Link Pass-Through the state of the 100Base-TX receiver is passed to the 100Base-X transmitter to make the media converter appear transparent to the end devices that are connected. In addition, if Far-End Fault is enabled the media converter can turn off the 100Base-TX transmitter when a FAR-End Fault is received.

Using Link Pass-Through with Far-End Fault minimizes data loss when a fault occurs. Should a fault occur, the end devices have the indication of a failure available to them making trouble shooting easier.

---

## Far-End Fault (FEF)

---

The media converter implements the 802.3 standard for Far-End Fault for the indication and detection of remote fault conditions on the 100Base-X fiber connection. With Far-End Fault enabled the media converter transmits the Far-End Fault Indication over the 100Base-X fiber connection whenever a receive failure is detected on the 100Base-X fiber connection. The media converter continuously monitors the 100Base-X fiber connection for a valid signal.

The action the media converter takes on receiving a Far-End Fault Indication is dependent on the Link Pass Through switch setting.

---

## Duplex

---

Full and half duplex operation supported.

---

## Pause (IEEE 802.3xy)

---

Pause signaling is an IEEE feature that temporarily suspends data transmission between two devices in the event that one of the devices becomes overwhelmed. The fast ethernet media converter supports pause negotiation on the 100Base-TX copper connection.

---

## VLAN

---

The media converter is transparent to VLAN tagged packets.



---

## Remote LoopBack

---

The media converter is capable of performing a loopback on the fiber port.

---

Specifications	
<b>Lifetime limited warranty</b>	<b>Reach, RoHS and WEEE Compliant</b>
<b>HTSUS Number:</b> 8517.62.0020	<b>UNSPSC Code:</b> 43201553
<b>ECCN:</b> 5A991	
	
Power	
Input Supply Voltage	Triple voltage 12 / 24 / 48 VDC (9.6 – 60 VDC) input supporting: a) 2 x Terminal Block power input and b) 1 x T-Bus power input
Current	0.09 A (@ 24VDC)
Power Consumption	2.16 watts (@ 24VDC)
Power Connector	Dual input Terminal Block and/or T-Bus
Indicators	
Power / TST	This green LED is turned on when power is applied to the media converter. Otherwise it is off. The LED will blink fast/slow when in Loopback test mode or hardware error.
Fiber link on / Receive activity (LKF)	On: Fiber link present. Blinking slowly: Fiber link disabled because of copper link loss. Blinking quickly: Fiber link present and receiving data. Off: No fiber link present
Copper link on / Receive activity (LKC)	On: Copper link is present. Blinking quickly: Copper link present and receiving data. Blinking slowly: Copper link disabled because of fiber link loss. Off: No copper link present

Switches - accessible by sliding the chassis open



**Auto-Negotiation**

**Auto (Default - Up):** In this mode of operation the media converter will negotiate Ethernet parameters on the copper connection. This will ensure the most optimal connection parameters will be in effect. If the copper link partner does not support Auto negotiation, the media converter will default to 100 Mbps and Half Duplex mode.

**Off:** Auto Negotiation should only be turned off, if the copper link partner does not support Auto Negotiation. When the Auto Negotiation switch is set to the OFF position, the media converter will operate at 100 Mbps and Full Duplex mode.

**Smart Link Pass-Through**

**Smart Link Pass-Through (Default - Up):** In this mode, the link state on one connection is directly reflected through the media converter to the other connection. If link is lost on one of the connections, then the other link will be brought down by the media converter. If the installation has a media converter on both ends of the fiber link and both are setup for Link Pass-Through, then a loss of copper link on the far end device will propagate through both media converters and will result in a loss of copper link at the near end device. This would, therefore, resemble a direct copper connection.

**Standard Mode (Down):** In this mode, the links on the fiber and copper sides can be brought up and down independently of each other. A loss of link on either the fiber ports or copper ports can take place without affecting the other connection

**Pause**

**Auto (Default-Up):** When Auto Negotiation has been set to Auto, the media converter will use this setting for its Ethernet parameter negotiation on the copper connection.

**Half:** The media converter will not negotiate support for the Pause feature.

<p>Loopback</p>	<p>Disabled (Default-Up): The loopback feature is disabled. This is the normal position for regular operation. The switch must be set to this position for data to pass through the media converter.</p> <p>Enabled: This is a test mode. All data received on the receive (RX) fiber connection is looped back to the transmit (TX) fiber connection. The state of the copper is not relevant and no data or link status is passed through to the copper side.</p>
<p>Far-End Fault (FEF)</p>	<p>Enabled (Default-Up): If the media converter detects a loss of fiber signal on the fiber receiver, it will immediately send a FEF on the fiber link. This notifies the fiber link partner that an error condition exists on the fiber connection. If the remote media converter is set up for FEF, and the local media converter is set up with Link Pass-Through, a loss of fiber link on either the transmit or receive line will be passed through to the local copper connection to notify the connected device. If the media converter has been set to Link Pass-Through mode, the effect will be the same as FEF since the link loss on the fiber receiver will bring down the copper link, which will in turn cause the transmit fiber link to be brought down.</p> <p>Disabled: The media converter will not monitor for or generate Far End Fault.</p>
<p>Cables and Connectors</p>	
<p>100Base-TX</p>	<p>RJ45 connector, 2 pair CAT 5 (UTP or STP) or better cable</p>
<p>Fixed Fiber</p>	<p>Dual multimode or single mode ( Duplex ) fiber - SC, ST Single strand fiber ( Simplex ) – SC, ST</p>
<p>Magnetic Isolation</p>	<p>1.5kv</p>
<p>Fiber Optic Cable</p>	<p>Multimode: 62.5 / 125, 50/125, 85/125, 100/140 micron Single Mode: 9/125 micron (ITU-T 625)</p>
<p>Filtering</p>	
<p>Filtering</p>	<p>1024 MAC Addresses</p>
<p>Frame Specifications</p>	
<p>Buffer</p>	<p>512 Kbits frame buffer memory</p>
<p>Size</p>	<p>Maximum frame size of 2048 bytes</p>

<b>Packet Transmission Characteristics</b>	
Bit Error Rate (BER)	<10 <sup>-12</sup>
<b>Environmental Specifications</b>	
Operating Temperature	-10°C to 60°C (14°F to 140°F)
Storage Temperature	-25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing
Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output ( BTU/HR )	7.37
MTBF (Hours)	694,621 (Calculation model based on MIL-HDBK-217-FN2 @ 30 °C)
Chassis	Molded plastic DIN Rail case with an IP20 ingress protection rating
<b>Mounting</b>	
Din Rail Kit	Native
<b>Product Weight and Dimensions</b>	
Weight	0.12 kg, 0.26 lbs
Dimensions	114 x 100 x 22.5mm, 4.5 x 3.9 x 0.88 inches
<b>Packaging</b>	
Shipping Weight	0.17 kg, 0.37 lbs
Shipping Dimensions	145 x 105 x 30 mm, 5.7 x 4.1 x 1.2 inches

Regulatory Approvals	
Emissions	FCC 47 Part 15 Class A EN55011 (CISPR11) ICES-003 EN61000-6-4 (Emissions for industrial environments) CISPR 32 / EN 55032 EN61000-3-2
Immunity	CISPR 35 / EN 55035 EN 61000-4-2 (ESD) EN 61000-4-3 (RS) EN 61000-4-4 (EFT) EN 61000-4-5 (Surge) EN 61000-4-6 (CS) EN 61000-4-8 (PFMF) EN 61000-4-11 IEC/EN 61000-6-2 (General Immunity for Industrial Environments)
Safety	UL/EN/IEC 62368-1 (previously 60950-1) CAN/CSA C22.2 No. 62368-1 CE
Laser Safety	EN 60825-1 Fiber optic transmitters on this device meet Class 1 Laser safety requirements per IEC-60825 FDA/CDRH standards and comply with 21CFR1040.10 and 21CFR1040.11.

## Product List

---



**SR-100-SC2-** Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100BASE-FX 1310nm multimode (SC) [2 km/1.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

### Power Cord & Part Number(s)

None

**05091010**

---



**SR-100-ST2-** Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100BASE-FX 1310nm multimode (ST) [2 km/1.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

### Power Cord & Part Number(s)

None

**05091000**

---



**SR-100-SC20-** Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-LX 1310nm single mode (SC) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

### Power Cord & Part Number(s)

None

**05091020**

---



**SR-100-ST20**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-LX 1310nm single mode (ST) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091030**

---



**SR-100-SC40**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-EX 1310nm single mode (SC) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091040**

---



**SR-100-ST40**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-EX 1310nm single mode (ST) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091050**

---



**SR-100-SC80**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-ZX 1550nm single mode (SC) [80 km/49.7 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091060**

---



**SR-100-ST80**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-ZX 1550nm single mode (ST) [80 km/49.7 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091070**

---



**SR-100-SC120**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-ZX 1550nm single mode (SC) [120 km/74.6 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091080**

---



**SR-100-ST120**- Fast Ethernet Industrial Media Converter: 100BASE-TX (RJ-45) [100 m/328 ft] to 100Base-ZX 1550nm single mode (ST) [120 km/74.6 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091090**

---



**SR-100-SC2D**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1550nm TX / 1310nm RX single strand fiber, multimode (SC) [2 km/1.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091140**

---



**SR-100-SC2U**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1310nm TX / 1550nm RX single strand fiber, multimode (SC) [2 km/1.2 miles]. DIN Rai case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091150**

---



**SR-100-ST2D**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1550nm TX / 1310nm RX single strand fiber, multimode (ST) [2 km/1.2 miles]. DIN Rai case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091180**

---



**SR-100-ST2U**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1310nm TX / 1550nm RX single strand fiber, multimode (ST) [2 km/1.2 miles]. DIN Rai case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091190**

---



**SR-100-SC20U**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1310nm TX / 1550nm RX single strand fiber, single mode (SC) [20 km/12.4 miles].DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091100**

---



**SR-100-SC20D**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1550nm TX / 1310nm RX single strand fiber, single mode (SC) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091110**

---



**SR-100-ST20U**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1310nm TX / 1550nm RX single strand fiber, single mode (ST) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091160**

---



**SR-100-ST20D**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1550nm TX / 1310nm RX single strand fiber, single mode (ST) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091170**

---



**SR-100-SC40U**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1310nm TX / 1550nm RX single strand fiber, single mode (SC) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

---

**Power Cord & Part Number(s)**

None

**05091120**

---



**SR-100-SC40D**- Fast Ethernet Industrial Media Converter: 100Base-TX (RJ-45) [100 m/328 ft] to 100Base-BX 1550nm TX / 1310nm RX single strand fiber, single mode (SC) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

**Power Cord & Part Number(s)**

None

**05091130**

**Related Accessories**

**Accessories**



Transmit power voltage and data across the bus. 4 parallel positions and 1 serial position. UL 8A / cUL 6A, 150 V. Width 22.5cm. Carton of 5. For use with SR and SRS DIN Rail Media Converters.

**22038528**

## Power Supplies



TRIO-PS/1AC/48DC/10 Power Supply - DIN-Rail 48 VDC , 480 Watt power supply with universal 85 to 264 VAC, 30 to 56V DC output range adjustable, -25 to 70°C extended

**28665018**



UNO-PS/1AC/24DC/60W DIN-Rail Power Supply: 24 VDC, 60 Watt with universal 85 to 264 VAC, -25 to 70°C extended operating temperature.

**29029928**



UNO-PS/1AC/24DC/150W Power Supply - DIN-Rail 24 VDC , 150 Watt power supply with universal 85 to 264 VAC, -25 to 70°C extended operating temperature

**29043768**