

SR-1110 DIN Rail Media Converters

Rate Converting Copper to Fiber Converters



- 10/100/1000Base-T to 1000Base-X Fiber Media Converters
- Connect 10/100 devices to Gigabit backbone
- Link copper to multimode or single mode fiber
- Dual fiber ST/SC or Single fiber SC connectors
- Extend network distances up to 160km
- Advanced Features: Link Pass-Through, Far-End Fault, Auto-MDIX
- Triple Power Input: Dual Terminal block power connector & T-Bus

Perle **SR-1110 DIN Rail Media Converters** transparently connect UTP copper to fiber. These rate converting Media Converters provide an economical path to:

- extend the life of non-fiber based equipment by enabling data transmission from 10/100/1000Base-T devices over gigabit fiber
- enable Gigabit speeds across a multimode fiber link up to 2km in length (**learn more**)
- extend the distance of an existing network by linking CAT5/6/7 cabling to multimode or single mode fiber
- extend the distance between two copper-based devices or networks
- protect Ethernet data from EMI noise and interference by inter-connecting your copper-Ethernet devices over fiber in industrial plants.

Some SR-1110 Media Converters are also available with **an SFP slot** or support for **-40°C to +75°C (-40°F to +167°F) extended operating temperatures**.

Network Administrators can rest assured with Perle's advanced features such as Auto-Negotiation, Auto-MDIX, Link Pass-Through, Far End Fault, and Pause which make the end to end link completely transparent. This allows for more efficient troubleshooting and less on-site maintenance. These cost and time saving features, along with a lifetime warranty and free worldwide technical support, make **SR-1110 Rate Converting Media Converters** the smart choice for IT professionals.

SR-1110 Fiber Media Converter Features: 10/100/1000Base-T to 1000Base-X

DIN Rail Enclosure

Easily mount on a DIN rail or inside distribution boxes using native DIN Rail enclosure with grounding clip. No need for add-on brackets.

Auto-Negotiation

The media converter supports auto negotiation. The 1000Base-X fiber interface negotiates according to 802.3 clause 37. The 10/100/1000Base-T negotiates according to 802.3 clause 28 and 40. The 1000Base-X will link up with its partner after the highest common denominator (HCD) is reached and the copper has linked up with its partner. The 1000Base-X will continue to cycle through negotiation transmitting a remote fault of offline (provided this is enabled through the switch setting) until the copper is linked up and the HCDs match.

The media converter supports auto-negotiation of full duplex, half duplex, remote fault, full duplex pause, asymmetric pause and Auto MDI-X.

Auto-MDIX

Auto-MDIX (automatic medium-dependant interface crossover) detects the signaling on the copper ethernet interface to determine the type of cable connected (straight-through or crossover) and automatically configures the connection when enabled. The media converter can also correct for wires swapped within a pair.

The media converter will adjust for up to 120ns of delay skew between the 1000Base-T pairs.

Smart Link Pass-Through

When Smart Link Pass-Through mode is enable, the Ethernet copper port will reflect the state of the Ethernet fiber media converter port. This feature can be used whether fiber auto-negotiation is enabled or disabled.

Fiber Fault Alert

With Fiber Fault Alert the state of the 1000Base-X receiver is passed to the 1000Base-X transmitter. This provides fault notification to the partner device attached to the 1000Base-X interface of the media converter. If the 1000Base-X transmitter is off, as a result of this fault, it will be turned on periodically to allow the condition to clear should the partner device on the 1000Base-X be using a similar technique. This eliminates the possibility of lockouts that occur with some media converters. Applies only when fiber auto-negotiation is disabled.

Pause (IEEE 802.3xy)

Pause signaling is an IEEE feature that temporarily suspends data transmission between two devices in the event that one of the devices becomes overwhelmed. The media converter supports pause negotiation on the 10/100/1000Base-T copper connection and 1000Base-X fiber connection.

Duplex

Full and half duplex operation supported.

Jumbo Packets



Transparent to jumbo packets up to 10KB.


VLAN

Transparent to VLAN tagged packets.

Remote Loopback

Capable of performing a loopback on the 1000Base-X fiber interface.

Specifications					
Lifetime limited warranty	<table border="0"> <tr> <td>Reach, RoHS and WEEE Compliant</td> <td>HTSUS Number: 8517.62.0020</td> <td>UNSPSC Code: 43201553</td> <td>ECCN: 5A991</td> </tr> </table>	Reach, RoHS and WEEE Compliant	HTSUS Number: 8517.62.0020	UNSPSC Code: 43201553	ECCN: 5A991
Reach, RoHS and WEEE Compliant	HTSUS Number: 8517.62.0020	UNSPSC Code: 43201553	ECCN: 5A991		
 					
Power					
Input Supply Voltage	Triple voltage 12 / 24 / 48 VDC (9.6 – 60 VDC) input supporting: <ul style="list-style-type: none"> • 2 x Terminal Block power input and • 1 x T-Bus power input 				
Current	0.09 A (@ 24VDC)				
Power Consumption	2.16 watts (@ 24VDC)				
Power Connector	Dual input Terminal Block and/or T-Bus				
Indicators					
Power / TST	This green LED is turned on when power is applied to the media converter. Otherwise it is off. The LED will blink fast/slow when in Loopback test mode or hardware error.				

<p>Fiber link on / Receive activity (LKF)</p>	<ul style="list-style-type: none"> • On: Fiber link present. • Blinking slowly: Fiber link disabled because of copper link loss. • Blinking quickly: Fiber link present and receiving data. • Off: No fiber link present
<p>Copper link on / Receive activity (LKC)</p>	<ul style="list-style-type: none"> • On: Fiber link present. • Blinking slowly: Fiber link disabled because of copper link loss. • Blinking quickly: Fiber link present and receiving data. • Off: No fiber link present
<p>Link Pass-Through (LKP)</p>	<ul style="list-style-type: none"> • On: Copper link is present. • Blinking slowly: Copper link disabled because of fiber link loss. • Blinking quickly: Copper link present and receiving data. • Off: No copper link present
<p>10/100/1000 Copper Speed (SP)</p>	<ul style="list-style-type: none"> • Green: 1000 Mbps • Yellow: 100 Mbps • Off: 10 Mbps
<p>Copper Link Activity (LK)</p>	<ul style="list-style-type: none"> • On: Copper link is present • Blinking quickly: Copper link receiving data
<p>Switches - accessible by sliding the chassis open</p>	
	
<p>Auto-Negotiation</p>	<ul style="list-style-type: none"> • Auto (Default-Up): In this mode of operation the media converter will negotiate Ethernet parameters on both the copper and the fiber connection. This will ensure the most optimal connection parameters will be in effect. If connecting to another Perle Gigabit Media Converter, this parameter should be set to Auto. • Off: Copper Negotiation should only be turned off, if the copper link partner does not support copper link negotiations.

<p>Smart Link Pass-Through</p>	<ul style="list-style-type: none"> • Smart Link Pass-Through (Default-Up): In this mode, the link state on one connection is directly reflected through the media converter to the other connection. If link is lost on one of the connections, then the other link will be brought down by the media converter. If the installation has a media converter on both ends of the fiber link and both are setup for Smart Link Pass-Through, then a loss of copper link on the far end device will propagate through both media converters and will result in a loss of link at the near end device. This would, therefore, resemble a direct copper connection. • Standard Mode (Down): In this mode the links on the fiber and copper sides can be brought up and down independently of each other. A loss of link on either the fiber link or copper link can take place without affecting the other connection.
<p>Loopback</p>	<ul style="list-style-type: none"> • Disabled (Default-Up): The loopback feature is disabled. This is the normal position for regular operation. The switch must be set to this position for data to pass through the media converter. • Enabled: This is a test mode. All data received on the receive (RX) fiber connection is looped back to the transmit (TX) fiber connection. The state of the copper is not relevant and no data or link status is passed through to the copper side.
<p>Fiber Fault Alert</p>	<ul style="list-style-type: none"> • Enabled (Default-Up): In this mode, when Fiber negotiation is turned on, if the media converter detects a loss of fiber signal on the fiber receiver it will immediately disable its fiber transmitter signal. This notifies the fiber link partner that an error condition exists on the fiber connection. If the remote media converter is set up for FFA Enabled and the local media converter is set up with Smart Link Pass-Through, a loss of fiber link on either the transmit or receive line will be passed through to the local copper connection to notify the connected device. If the media converter has been set to Smart Link Pass-Through mode, the effect will be the same as FFA since the link loss on the fiber receiver will result in bringing down the copper link, which will in turn cause the transmit fiber link to be brought down. • Disabled: In this mode, the media converter will not monitor for fiber fault.
<p>Duplex Mode</p>	<ul style="list-style-type: none"> • Full (Default-Up): In this mode, when Auto Negotiation is set to off, the media converter will be set to Full Duplex mode. • Half: The media converter will be set to Half Duplex mode

Copper Speed	<ul style="list-style-type: none"> • 100 (Default-Up): In this mode, when Auto Neg (copper) is set to off, the media converter will use this switch setting for its Ethernet copper speed connection. The media converter will force the speed to 100 Mbps. • 10: The media converter will force the speed to 10 Mbps
Cables and Connectors	
10/100/1000Base-T	RJ45 connector <ul style="list-style-type: none"> • 2 pair CAT 5 (UTP or STP) or better cable for 10/100 Mbps • 4 pair CAT 5 (UTP or STP) or better cable for 10/100/1000 Mbps
Fixed Fiber	<ul style="list-style-type: none"> • Dual multimode or single mode (Duplex) fiber - SC, ST • Single strand fiber (Simplex) – SC
Magnetic Isolation	1.5kv
Fiber Optic Cable	<ul style="list-style-type: none"> • Multimode: 62.5 / 125, 50/125, 85/125, 100/140 micron • Single Mode: 9/125 micron (ITU-T 625)
Filtering	
Filtering	1024 MAC Addresses
Frame Specifications	
Buffer	1000 Kbits frame buffer memory
Size	<ul style="list-style-type: none"> • Maximum frame size of 10,240 bytes -- Gigabit • Maximum frame size of 2048 bytes -- Fast Ethernet
Packet Transmission Characteristics	
Bit Error Rate (BER)	$<10^{-12}$
Environmental Specifications	
Operating Temperature	-10°C to 60°C (14°F to 140°F)
Storage Temperature	-25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing

Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output (BTU/HR)	7.37
MTBF (Hours)	564,766 Hours <i>Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>
Chassis	Molded plastic DIN Rail case with an IP20 ingress protection rating
Mounting	
Din Rail Kit	Native
Product Weight and Dimensions	
Weight	0.12 kg, 0.26 lbs
Dimensions	114 x 100 x 22.5mm, 4.5 x 3.9 x 0.88 inches
Packaging	
Shipping Weight	0.17 kg, 0.37 lbs
Shipping Dimensions	145 x 105 x 30 mm, 5.7 x 4.1 x 1.2 inches
Regulatory Approvals	
Emissions	<ul style="list-style-type: none"> • FCC 47 Part 15 Class A • EN55011 (CISPR11) • ICES-003 • EN61000-6-4 (Emissions for industrial environments) • CISPR 32 / EN 55032 • EN61000-3-2
Immunity	<ul style="list-style-type: none"> • CISPR 35 / EN 55035 • EN 61000-4-2 (ESD) • EN 61000-4-3 (RS) • EN 61000-4-4 (EFT) • EN 61000-4-5 (Surge) • EN 61000-4-6 (CS) • EN 61000-4-8 (PFMF) • EN 61000-4-11 • IEC/EN 61000-6-2 (General Immunity for Industrial Environments)

<p>Safety</p>	<ul style="list-style-type: none"> • UL/EN/IEC 62368-1 (previously 60950-1) • CAN/CSA C22.2 No. 62368-1 • CE
<p>Laser Safety</p>	<ul style="list-style-type: none"> • EN 60825-1 • Fiber optic transmitters on this device meet Class 1 Laser safety requirements per IEC-60825 FDA/CDRH standards and comply with 21CFR1040.10 and 21CFR1040.11.

Product List



SR-1110-SC05- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-SX 850nm multimode (SC) [550 m/1804 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091640



SR-1110-ST05- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-SX 850nm multimode (ST) [550 m/1804 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091650



SR-1110-SC2- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-LX 1310nm Extended multimode (SC) [2km /6562 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091660



SR-1110-ST2- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-LX 1310nm Extended multimode (ST) [2km /6562 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091670



SR-1110-SC10- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-LX/LH 1310 nm single mode (SC) [10 km/6.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091680



SR-1110-ST10- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-LX/LH 1310 nm single mode (ST) [10 km/6.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external po

Power Cord & Part Number(s)

None

05091690



SR-1110-SC40- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-EX 1310 nm single mode (SC) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091700



SR-1110-ST40- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-EX 1310 nm single mode (ST) [40 km/24.9 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091710



SR-1110-SC70- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (SC) [70 km/43.5 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091720



SR-1110-ST70- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (ST) [70 km/43.5 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091730



SR-1110-SC120- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (SC) [120 km/74.6 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091750



SR-1110-ST120- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (ST) [120 km/74.6 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091740



SR-1110-SC160- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (SC) [160 km/100 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091760



SR-1110-ST160- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-ZX 1550 nm single mode (ST) [160 km/100 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091770



SR-1110-SC05U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1310nm TX / 1550nm RX single strand fiber, multimode (SC) [500 m/1640 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091890



SR-1110-SC05D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1550nm TX / 1310nm RX single strand fiber, multimode (SC) [500 m/1640 ft]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091880



SR-1110-SC10U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [10 km/6.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091780



SR-1110-SC10D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [10 km/6.2 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091790



SR-1110-SC20U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091800



SR-1110-SC20D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [20 km/12.4 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091810



SR-1110-SC40U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [40 km/25 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091820



SR-1110-SC40D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [40 km/25 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091830



SR-1110-SC80U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1510nm TX / 1590nm RX single strand fiber, single mode (SC) [80 km/50 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091840



SR-1110-SC80D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1590nm TX / 1510nm RX single strand fiber, single mode (SC) [80 km/50 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091850



SR-1110-SC120U- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1510nm TX / 1590nm RX single strand fiber, single mode (SC) [120 km/75 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091860



SR-1110-SC120D- 10/100/1000 Industrial Media and Rate Converter: 10/100/1000BASE-T (RJ-45) [100 m/328 ft] to 1000BASE-BX 1590nm TX / 1510nm RX single strand fiber, single mode (SC) [120 km/75 miles]. DIN Rail case, terminal block (Combicon) power connector for external power source

Power Cord & Part Number(s)

None

05091870

Related Accessories

Accessories



Transmit power voltage and data across the bus. 4 parallel positions and 1 serial position. UL 8A / cUL 6A, 150 V. Width 22.5cm. Carton of 5. For use with SR and SRS DIN Rail Media Converters.

22038528

Power Supplies



TRIO-PS/1AC/48DC/10 Power Supply - DIN-Rail 48 VDC , 480 Watt power supply with universal 85 to 264 VAC, 30 to 56V DC output range adjustable, -25 to 70°C extended

28665018



UNO-PS/1AC/24DC/60W DIN-Rail Power Supply: 24 VDC, 60 Watt with universal 85 to 264 VAC, -25 to 70°C extended operating temperature.

29029928



UNO-PS/1AC/24DC/150W Power Supply - DIN-Rail 24 VDC , 150 Watt power supply with universal 85 to 264 VAC, -25 to 70°C extended operating temperature

29043768