



DC Power Station 72000

Item no.:

421-22



EAN:



5 Years Warranty	72000 mAh
-------------------------------	---------------------

100% Charging status display	Charge multiple devices
---	----------------------------

2 x USB-C input / output	12V / 10A output
-----------------------------	---------------------

Powerful 6W LED lamp	Fast recharge by solar panels with DC5021 port
-------------------------	--

Supports MPPT solar charging

RoHS COMPLIANT	Recycling symbol
FCC	CE
WEEE symbol	Recycling symbol



Sandberg DC Power Station 72000 is your mobile power hub, with a capacity of 72,000 mAh / 270 Wh. You get two powerful 100W USB-C PD ports, two USB-A QC3.0 ports with up to 22W, and a 12V DC output, so you can charge your laptop, tablet, phone, and much more. All five outputs can be used simultaneously! It comes with both male and female adapters for the car's 12V socket, so you can easily connect car equipment, a cooler, or a pump directly. Supports charging via both USB-C and solar panel (MPPT) through the DC input. With a built-in LED lamp, you're ready for anything from camping to power outages.

More information:
 www.sandberg.world



Sandberg DC Power Station 72000

Specifications

Battery capacity: 24 Ah @ 11.25V = 270 Wh / 72000 mAh @ 3.75V = 270 Wh
Battery type: LiMnFePO₄ (LMFP)
Lifecycle: 2000+ cycles to 80%
USB-C PD input 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD input 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
DC input: 12V-26V / 100W (MPPT supported) (DC35135)
USB-C PD output 1: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-C PD output 2: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (100W max)
USB-A output 1: 5V/3A, 9V/2A, 12V/1.5A (18W max)
USB-A output 2: 5V/3A, 9V/2A, 12V/1.5A (18W max)
DC output: 9.6V-12.6V / 10A (DC5521)
Max total output power: 268W
LED light: Integrated 6W LED
Weight: Approx. 2.3 kg
Charge time: Approx. 3 hours with 100W PD charger (not included)

Supports pass-through charging with port-specific behavior:
If power is being input via DC IN, then USB-C1 cannot be used for input or output at the same time. Other ports work normally.
If USB-C1 is being used for input, DC IN cannot be used simultaneously. Other ports work normally.
If USB-C2 is used for input, USB-A2 can still provide output at the same time, up to 15W. Other ports work normally.



Packaging info

1 Sandberg DC Power Station 72000
1 12V car socket (male) adapter cable, 100 cm
1 12V car socket (female) adapter cable, 15 cm
1 USB-C to USB-C charging cable, 50 cm
1 Quick guide

Quick guide: <https://sandberg.world/mt/manual/421-22>

Dimensions

	Product	Package
Height (cm)	15.20	21.70
Width (cm)	16.50	20.30
Depth (cm)	6.20	10.80
Weight (g)	2,312.00	2,573.00



Product:
www.sandberg.world/product/dc-power-station-72000

Dealer:

