



100w Active Soundbar Plus

SB-1900P EU SAP: 4801694 US SAP: 13445515

vav.link/sb-1900p

Built-in 2 x 90 watts (PEAK) amplifier
HDMI 2 in 1 out
1 x Minijack input
Bluetooth input (re-nameable and pin can be set)
Remote control included
RS-232
ARC HDMI Input (allows display to control volume)

Need to punch a hole in the back wall? The SB-1900P soundbar outputs truly impressive sound! The chassis has a matt black finish that enhances any audio-visual installation in meeting rooms, boardrooms, and conference rooms.



Rename Bluetooth

Set any Bluetooth name and Pin. Use PC software to load an image file onto a USB stick. Insert into the soundbar and boot up.



Multiple HDMI

Two HDMI inputs and an HDMI output make connecting to other devices easy.



ARC HDMI

If a display is connected to the ARC input on the soundbar, the display remote control will control the soundbar volume.

Analogue Input

A stereo line-level Minijack input handles normal analogue sources.

RS-232 Control

For professional integration it features RS-232 control via the USB port.

Auto Standby

Choose to use the standard auto standby setting to conserve power, or hold down VOL+ to disable auto-standby.

Hanging Brackets

A set of brackets are included which hang the soundbar under the flat panel. The speaker also comes with rubber feet if you need to place on a shelf, and wall-hanging lugs.

Power Cycling

If mains power is turned off and on, the SB-1900P will automatically come back on resuming the previous settings.

Remote Control

A remote control is included.



MANUAL

Hanging bracket quick manual

EN PDF 110.37 KB

files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P_hanging_bracket_quick_manual.pdf

Manual

EN PDF 2.31 MB

files.visionaudiovisual.com/products/SB-1900P/manuals/SB-1900P_manual_en.pdf

Vision soundbar range overview

EN PDF 574.00 KB

files.visionaudiovisual.com/products/SB-1900P/product/Vision_soundbar_range_overview.pdf

CAD

Bracket

VND.DWG 803.57 KB

files.visionaudiovisual.com/products/SB-1900P/cad/SB-1900P_bracket.dwg

FIRMWARE

Firmware update added rs232

ZIP 867.69 KB

files.visionaudiovisual.com/products/SB-1900P/firmware/SB-1900P_firmware_update_added_rs232.zip

IMAGE

Product Images

ZIP 10.57 MB

<files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P.zip>

Product Images

PNG 1.45 MB

<files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P.png>

Rear

PNG 409.10 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_rear.png

Front

PNG 623.06 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_front.png

Hanging with display

PNG 1.15 MB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_hanging_with_display.png

Hanging

PNG 770.20 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_hanging.png

Psu

PNG 2.30 MB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_psu.png

Remote

PNG 2.65 MB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_remote.png

Line

PNG 6.53 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_line.png

Hanging brackets

PNG 606.02 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900_hanging_brackets.png

Wall brackets

PNG 506.07 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900B_wall_brackets.png

End

PNG 107.69 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_end.png

Serial cable

PNG 261.83 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_serial_cable.png

Menu

PNG 659.51 KB

files.visionaudiovisual.com/products/SB-1900P/images/SB-1900P_menu.png

SPECIFICATIONS

PRODUCT DIMENSIONS

800 x 90 x 62 mm / 31.5" x 3.5" x 2.4" (width x depth x height)

PACKAGED DIMENSIONS

1055 x 155 x 105 mm / 41.5" x 6.1" x 4.1"

PRODUCT WEIGHT

2.1 kg / 4.6 lbs

PACKAGED WEIGHT

3.6 kg / 7.9 lbs

CONSTRUCTION MATERIAL

ABS Plastic

COLOUR

Black

AMPLIFIER OUTPUT

2 x 90 watts (PEAK) / 2 x 50w watts (RMS)

DRIVERS

4

DRIVER IMPEDANCE

4 Ohms

INPUT 1

Aux in (3.5mm) Input Sensitivity: 700mV

INPUT 2

HDMI(2 in 1 out)

TOTAL HARMONIC DISTORTION

1% (1kHz, 1W)

USB-A

for renaming Bluetooth and RS-232 control

SPEAKER IMPEDANCE

8 ohms

SENSITIVITY

91 dB (1w/1m)

FREQUENCY RESPONSE

(-3dB) 70Hz-20kHz

POWER CONSUMPTION

30w (<0.5W standby)

BLUETOOTH

V4.2

MAXIMUM POWER TRANSMITTED

<5 dBm

FREQUENCY BANDS

2402 - 2480 MHz

POWER INPUT

DC 20V/3A

REMOTE CONTROL

Distance: 6 m (20ft) Angle: 30° Battery Type: CR 2025

ACCESSORIES INCLUDED

1 x Remote Control 2 x L shaped universal mounting strips – to hang soundbar beneath flat panel
1 x USB-A to 9-pin serial adaptor cable, Black 4 x 1.5 m (4.9ft) Figure-8 power cable (right-angle plug: UK/EU/US, normal plug: AU), Black

POWER SUPPLY

External 100-240v 50/60Hz AC Power Supply – 21 volt / 3 amp. DC tail length: 1.2 m (3.9ft).
Transformer dimensions: 128.9 x 51.3 x 34.8 mm (5.07" x 2.02" x 1.37"), Pin dimensions: Length: 10mm, diameter 6.5mm

WARRANTY

Lifetime return-to-base

COMPLIANCE

RoHS, WEEE, CE/EMC, FCC, IEC, RCM-POC, RCM-SDOC, REACH

ORDER PART CODE

SB-1900P [EU SAP: 4801694 / US SAP: 13445515]

SPARE POWER SUPPLY

TC2 P21V3A [EU SAP: 4873762 / US SAP: 13445527]

SPARE REMOTE

SB-1900P RC [EU SAP: 4873590/ US SAP: 13445517]

