

8		7		6		5		4		3		2		1	
Technical requirement 技术参数： 1. Electrical Characteristics Test电气性能检验 1.1 Products 100% for electrical test.成品100%电性测试。 1.2 Insulation resistance: Less than 15MΩ of 500V DC /1S. 绝缘阻抗:大于或等于15MΩ 500V DC/1S 1.3 Dielectric strength 耐电压 1.3.1 Between two conductors 2500 ⁺²⁰⁰ ₀ V AC for1.0s Trip-current 1.0mA max. 导体与导体之间2500 ⁺²⁰⁰ ₀ V AC /1秒,漏电流1.0mA(max)。 1.3.2 Between conductor and body 2500 ⁺²⁰⁰ ₀ V AC for 1.0s Trip-current 1.0mA max. 导体与本体之间2500 ⁺²⁰⁰ ₀ V AC /1秒,漏电流1.0mA(max)。 2. Finished product conditions 成品状态 2.1 The attachment plug front show the test mark of "T". 插头主视面须有测试标志"T"。 2.2 The dimension with "▽" must be control and inspected importantly. 带"▽"尺寸需重点管控和检验。 3.3 material and product comply with Doc No."QW-Q-043" 《material-and product- of restricted substance control specification. 物料及成品必须符合QW-Q-043《材料与成品限用物质管理规范》。 4. The standards for the products:.产品标准： 4.1 The socket-outlet shall comply with BS 1363-1:1995 and BS16363-2:1995. 插板须符合BS 1363-1:1995和BS1363-2:1995..										REV.	DESCRIPTION		DESIGN	APPROVAL	DATE
										X	NEW		Betty	B.G YANG	2014.10.23
															