



Configuration:

LA-207-01 12 VDC Replacement Power Supply for LT-800 (North America)*

LA-207-02 12 VDC Replacement Power Supply for LT-800 (Asia, UK)*

LA-207-03 12 VDC Replacement Power Supply for LT-800 (Euro)*

LA-207-04 12 VDC Replacement Power Supply for LT-800 (Australia)*

*01, 02, 03, and 04 designation refers to international plug type (type B, G, F, and I) for the power supply.

Product Overview:

Compatible with our LT-800 Stationary Transmitter, the LA-207 replacement power supply has four different line cord configurations to allow for use in nearly any region of the world.

Highlights:

- Safe, reliable 12 VDC power for the LT-800 transmitter
- Available with four user-selectable line cord configurations for use in nearly any region
- Backed by a 1 year warranty

Includes:

One (1) LA-207 12 VDC Replacement Power Supply for LT-800
One (1) Line cord

Product Specification: 12 VDC Replacement Power Supply for LT-800	
Power	
Power Supply Input	100-240V, 50-60 Hz, 1A
Power Supply Output	12 VDC, 1.66A 19.9 W
Power Supply Connector	.022 in (5.5mm) OD, .01 in (2.5 mm) ID, barrel type
Power Supply Type	In Line
Physical	
Color	Black
Shipping Weight	1 lb. (0.5 kg)
Cable Length	Power Supply Cable: 47.3 in. (120 cm) Line Cord: 72 in. (183 cm)
Dimensions (H x W x D)	3.86 in. x 1.81 in. x 1.22 in. (98 mm x 46 mm x 31 mm)
Weight	(-01) 13.2 oz. (373 g), (-02) 15 oz. (424 g), (-03) 14.5 oz. (410 g), (-04) 15 oz. (424 g)

Product Specification: 12 VDC Replacement Power Supply for LT-800	
Compliance	
Power Supply Compliance	UL, CUL, TUV, CB, CE, FCC, BSMI, CU, RCM, PSE, CCC, RoHS