

User Guide for the IR Shot Commander Remote

August 2022

The remote provides basic camera control for fixed cameras. In multi-camera environments, it also enables you to select which camera to control.








Before you can use the remote, you will need to install the batteries.

Installing the Batteries

The remote uses two AAA batteries.

1. Remove the cover from the back of the remote. You may need to press down on the upper edge while sliding it off.
2. Install the batteries as shown in the diagram in the battery opening.
3. Slide and snap the cover back into place.

IR Shot Commander Remote Quick Reference

	<p>Data Screen button – Press to display the camera’s IP and MAC addresses on the video output(s); press again to dismiss the information display.</p> <p>OSD button – Press to display the camera’s IP and MAC addresses on the video output; press again to dismiss the information display.</p>
	<p>Power button and indicator – Set the camera to standby mode, or return to full-power mode.</p>
	<p>Arrow buttons – Pan and tilt.</p>
	<p>OK button – Return to the camera's home zoom level.</p>
	<p>Zoom Out (–) and Zoom In (+) buttons – Decrease or increase the zoom.</p>
	<p>IR1, IR2, and IR3 buttons – Select IR channel 1, 2, or 3. Vaddio cameras default to camera 1.</p>
	<p>P-Store and Preset buttons – Store and recall zoom presets.</p>



Storing Presets

Set up the shot. Then hold down the **P-Store** button while pressing **Preset 1** or **Preset 2**.



Tips for Using the Remote

Presets: The remote provides access to camera presets. Your camera's web interface may provide access to additional camera presets.

Camera selection: The remote has three IR channels, so it can control up to three cameras independently. Check your camera's manual for information on setting it as camera 1, camera 2, or camera 3. By default, Vaddio cameras respond as camera 1

Troubleshooting tip: If the camera does not respond to the remote, press the Camera 1 button and try again. If that doesn't fix the problem, try the other camera selection buttons.

Vaddio is a brand of Legrand AV Inc. · www.legrandav.com · Phone 800.572.2011 / +1.763.971.4400 · Fax +1.763.971.4464 · Email av.vaddio.support@legrand.com

Vaddio is a registered trademark of Legrand AV Inc. All other brand names or marks are used for identification purposes and are trademarks of their respective owners. All patents are protected under existing designations. Other patents pending.

©2022 Legrand AV Inc.